

Technical Data Sheet Rev 06-240923

10 Port GL 3523 Hub PCBA w/ LED Indicators & High Current Output

Model Number: CG-10A33523-PCBA



Features

- **Protect Your Equipment:** The 10-port hub features 20kV ESD surge protection to keep your connected peripherals safe from harm.
- **Super Fast Speeds:** This USB hub is 3.2 Gen 1 compliant, ensuring super-fast 5Gbps data transfer speeds. It supports super speed, high speed and full speed which enables it to be compatible with USB 2.0 / 1.1.
- **Upstream:** 1 USB port, Type B connector
- **Downstream:** 10 USB ports, Type A connectors
- **Power Connector:** DC Barrel & 6-Pin Molex Power Connector. Input Voltage: 12 ~ 24V DC

Package Contents

- Hub - Board Only

Specifications

OVERVIEW

Model No	CG-10A33523-PCBA
Product Type	USB Charger Hub
Compliance	None or N/A
UPC	045079163805
Country of Origin	China
LED indicators	None or N/A
Chipset	GL3523
Electrical Protections	N/A

PHYSICAL

Ship Weight (lbs)	0.16 lbs
Ship Weight (kg)	0.07 kg
Length	6.04 inches
Width	1.58 inches
Height	0.67 inches
Material	N/A
Mountable	Bare PCB

Specifications Cont.

CONNECTIONS

Upstream Port Type	USB 3.2G1 / 3.0 Type-B Female
Downstream Port Count	10
Downstream Port Type	10x Type A USB 3.2 G1 / 3.0

POWER

Input Voltage	12 ~ 24V DC
Power Connector	DC barrel, 2.5 ID x 5.5 OD, Center Pin Positive

ENVIRONMENTAL

Operating Temperature	0C ~ 60C
Storage Temperature	-20C ~ 70C
Operating Humidity	15 ~ 85% RH

OS SUPPORT

Supported Operating Systems	OS independent - No software or drivers required
-----------------------------	--

WARRANTY

Warranty Period	1 Year
-----------------	--------

PRODUCT URL

Product Page	https://www.coolgear.com/product/10-port-gl-3523-hub-pcba-w-led-indicators-high-current-output
--------------	---

USB CHARGING & CONNECTIVITY EXPERTS

We Speak Your Speak



When you reach out to Coolgear support, you'll find yourself in the hands of a solution-oriented and knowledgeable expert ready to answer whatever question you throw at them. Go ahead, test us.

[Visit Support](#)