



Technical Data Sheet Rev 06-250318

ChargeIT! mini 99W Dual Port USB-A & USB-C PD Charger PCBA w/ PPS & QC 4.0, UL & IEC Compliant

Model Number: CG-PD99UL-PCBA









Features

- Compact form factor and 2-Pin Phoenix connector enable easy installation in vehicles, control systems, kiosks, and more.
- High-Power USB-C PD Charging supports up to 99W combined output (20V 4.69A) with USB PD 3.0, PPS, and QC 4.0 compatibility
- Wide Input Voltage range accepts +9~24V DC for use in consumer and industrial vehicles.
- · Ideal for commercial and industrial vehicles, fleet systems, kiosks, and embedded power applications.
- · Rigorously tested to meet the highest international safety standards including CE, FCC, IEC, RoHS, and UL.

Package Contents

- 2-Pin Terminal Block
- · Charger Board Only

Specifications

OVERVIEW	
----------	--

OVERVIEW				
Model No	CG-PD99UL-PCBA	Product Type	OEM Boards	
Compliance	CE FCC IEC RoHS UL	UPC	045079164925	
Country of Origin	China	LED indicators	None or N/A	
Electrical Protections	15KV			

PHYSICAL

Ship Weight (lbs)	0.04 lbs	Ship Weight (kg)	0.02 kg
Item Weight	0.037 lbs	Length	1.93 inches
Width	1.78 inches	Height	0.52 inches
Material	N/A	Color	Black
Mountable	Bare PCB		



Specifications Cont.				
CONNECTIONS				
Downstream Port Count	2			
Downstream Port Type	1x Type A (Charging) 1x Type C (Charging)			
POWER				
Input Voltage	9 ~ 24V DC			
Power Connector	DC barrel, 2.5 ID x 5.5 OD, Center Pin Positive			
Supported Charge Protocols	Apple Charge 2.4A DCP FCP QC 3.0 / 2.0 Samsung			
Charging Details	5V/5A, 9V/3A, 15V/3A, 20V/4.69A			
OS SUPPORT				
Supported Operating Systems	OS independent - No software or drivers required			
WARRANTY				
Warranty Period	1 Year			
PRODUCT URL				
Product Page	https://www.coolgear.com/product/chargeit-mini-99w-dual-port-usb-a-usb-c-pd-charger-pcba-pps-qc-4-0-ul-iec-tested			

USB CHARGING & CONNECTIVITY EXPERTS

We Speak Your Speak



When you reach out to Coolgear support, you'll find yourself in the hands of a solution-oriented and knowledgeable expert ready to answer whatever question you throw at them. Go ahead, test us.

Visit Support